AD-A226 291

REPORT DOCUMENTATION PAGE

IRICI ASS--	1b. RESTRICTIVE MARKINGS
......-----v AUTHORITY	3. DISTRIBUTION/AVAILABILITY OF REPORT
2b. DECLASSIFICATION/DOWNGRADING SCHEDULE	Approved for public release; distribution unlimited.

4. PERFORMING ORGANIZATION REPORT NUMBER(S)	5. MONITORING ORGANIZATION REPORT NUMBER(S)
	ARo 23836.12-EC

6a. NAME OF PERFORMING ORGANIZATION	6b. OFFICE SYMBOL (If applicable)	7a. NAME OF MONITORING ORGANIZATION
University of Michigan		U. S. Army Research Office

6c. ADDRESS (City, State, and ZIP Code)	7b. ADDRESS (City, State, and ZIP Code)
1301 Beal Avenue EECS Department, Radiation Laboratory Ann Arbor, MI 48109-2122	P. O. Box 12211 Research Triangle Park, NC 27709-2211

8a. NAME OF FUNDING/SPONSORING ORGANIZATION	8b. OFFICE SYMBOL (If applicable)	9. PROCUREMENT INSTRUMENT IDENTIFICATION NUMBER
U. S. Army Research Office		DAAL03-87-K-0088

8c. ADDRESS (City, State, and ZIP Code)	10. SOURCE OF FUNDING NUMBERS			
P. O. Box 12211 Research Triangle Park, NC 27709-2211	PROGRAM ELEMENT NO.	PROJECT NO.	TASK NO.	WORK UNIT ACCESSION NO.

11. TITLE (Include Security Classification)

Via-Slot Coupling of Shielded Microstrip Lines

12. PERSONAL AUTHOR(S)
T.G. Livernois, L.P.B. Katehi

13a. TYPE OF REPORT	13b. TIME COVERED		14. DATE OF REPORT (Year, Month, Day)	15. PAGE COUNT
Interim Technical	FROM	TO	1988, April	24

16. SUPPLEMENTARY NOTATION
The view, opinions and/or findings contained in this report are those of the author(s) and should not be construed as an official Department of the Army position, policy, or decision, unless so designated by other documentation.

17. COSATI CODES			18. SUBJECT TERMS (Continue on reverse if necessary and identify by block number)
FIELD	GROUP	SUB-GROUP	

19. ABSTRACT (Continue on reverse if necessary and identify by block number)

Solution of complicated boundary value problems in the spectral domain is a very well known technique. Several years ago Itoh and Mittra used spectral analysis to solve planar geometry problems occurring in microwave integrated circuits. There have been numerous papers subsequently published utilizing this method. In this paper, Fourier analysis is used to formulate the solution for reflected and transmitted surface current densities in back to back shielded microstrip structures coupled by a transverse slot in their common wall. By applying Galerkin's procedure in the spectral domain on complementary field quantities, a solvable system of equations containing the desired reflection and transmission coefficient results.

20. DISTRIBUTION/AVAILABILITY OF ABSTRACT	21. ABSTRACT SECURITY CLASSIFICATION
☐ UNCLASSIFIED/UNLIMITED ☐ SAME AS RPT. ☐ DTIC USERS	Unclassified

22a. NAME OF RESPONSIBLE INDIVIDUAL	22b. TELEPHONE (Include Area Code)	22c. OFFICE SYMBOL

DD FORM 1473, 84 MAR
83 APR edition may be used until exhausted.
All other editions are obsolete.

SECURITY CLASSIFICATION OF THIS PAGE
UNCLASSIFIED

VIA-SLOT COUPLING OF SHIELDED MICROSTRIP LINES

by

T.G. Livernois
L.P.B. Katehi

April 1988

"VIA-SLOT COUPLING OF SHIELDED MICROSTRIP LINES"

by

T.G. Livernois
P.B. Katehi

April 1988

I. INTRODUCTION

Solution of complicated boundary value problems in the spectral domain is a very well known technique. Several years ago Itoh and Mittra used spectral analysis to solve planar geometry problems occurring in microwave integrated circuits, [1]. There have been numerous papers subsequently published utilizing this method, [2]. In this paper, Fourier analysis is used to formulate the solution for reflected and transmitted surface current densities in back to back shielded microstrip structures coupled by a transverse slot in their common wall. By applying Galerkin's procedure in the spectral domain on complementary field quantities, a solvable system of equations containing the desired reflection and transmission coefficient results.

II. THEORY

Application of the Galerkin method on the spectral domain electromagnetic quantities supported by the structure illustrated in Figure 1 requires a matrix equation which expresses electric and magnetic fields in terms of complement source densities. The appropriate expression is given in equation (1).

$$
\begin{bmatrix}
\tilde{E}_z^{(1a)}(\alpha, h_a, \beta) \\[2ex]
\tilde{H}_z^{(1a)}(\alpha, 0, \beta) \\[2ex]
\tilde{E}_z^{(1b)}(\alpha, -h_b, \beta)
\end{bmatrix}
=
\begin{bmatrix}
\tilde{G}_{11}(\alpha,\beta) & \tilde{G}_{12}(\alpha,\beta) & \tilde{G}_{13}(\alpha,\beta) \\[2ex]
\tilde{G}_{21}(\alpha,\beta) & \tilde{G}_{22}(\alpha,\beta) & \tilde{G}_{23}(\alpha,\beta) \\[2ex]
\tilde{G}_{31}(\alpha,\beta) & \tilde{G}_{32}(\alpha,\beta) & \tilde{G}_{33}(\alpha,\beta)
\end{bmatrix}
\begin{bmatrix}
\tilde{K}_{z_a}(\alpha, h_a, \beta) \\[2ex]
\tilde{M}_{x_a}(\alpha, 0, \beta) \\[2ex]
\tilde{K}_{z_b}(\alpha, -h_b, \beta)
\end{bmatrix}
$$

(1)

1

Explicit expressions for the $\tilde{G}_{ij}(\alpha,\beta)$, along with an outline

of their derivation are given in Appendix A. In this derivation,

we have assumed narrow microstrip lines and a narrow coupling

slot. These acceptable restrictions allow us to assume

uni-directional surface current densities which have a Maxwellian

distribution in the direction of their narrow dimension, [3].

Recent theoretical and experimental research by Dunleavy has shown

that the narrow microstrip line current variation mentioned above

is very accurate, [4]. Unfortunately, no such verification exists

for a magnetic current on a narrow aperture. However, since a

narrow microstrip line supporting an electric current and a narrow

aperture supporting a magnetic current are eseentially dual

quantities, [5], it seems that an assumed Maxwellian distribution

for the aperture problem would be accurate.

III. SPECTRAL DOMAIN REPRESENTATION OF CURRENT DENSITIES

The detailed geometry of this problem is given in Figure

2. In the spatial domain the two electric surface current

densities away from the discontinuities are written as:

$$K_{z_a}(x',h_a,z') = \left(e^{\gamma_{z_a}^{ms}z'} - Re^{-\gamma_{z_a}^{ms}z'} \right) g_a(x') \qquad z' \geq z_o$$

$$K_{z_b}(x',-h_b,z') = Te^{\gamma_{z_b}^{ms}z'} g_b(x') \qquad z' \leq -z_o$$

(2)

where

$$g_i(x') = \begin{cases} \dfrac{2}{\pi W_i} \left\{ 1 - \left[\dfrac{2(x'-x_i)}{W_i} \right]^2 \right\}^{-1/2} & -\dfrac{W_i}{2} \leq x'-x_i \leq \dfrac{W_i}{2} \\ \\ 0 & \text{Otherwise} \end{cases} \qquad (i = a, b)$$

$$(3)$$

It should be mentioned that $\gamma_{z_a}^{ms}$ and $\gamma_{z_b}^{ms}$ are known constants for their respective guiding structures. Their values may be obtained from the literature, [2]. In the vicinity of the discontinuities, all surface current densities in equation (1) must be expressed in terms of appropriate basis functions.

$K_{z_a}(x', h_a, z')$ and $K_{z_b}(x', -h_b, z')$ are written in the spatial domain as

$$K_{z_i}(x', h_i, z') = \sum_{n=1}^{N} I_{n_i} \, g_i(x') \, f_{n_i}(z') \quad i = a, b \qquad (4)$$

Where the I_{n_i} are unknown amplitudes and

$$f_{n_i}(z') = \begin{cases} \dfrac{\sin\left[K(z'-z_n-1) \right]}{\sin(Kl_z)} & z_{n-1} \leq z' \leq z_n \\ \\ \dfrac{\sin\left[K(z_{n+1}-z') \right]}{\sin(Kl_z)} & z_n \leq z' \leq z_{n+1} \\ \\ 0 & \text{Otherwise} \end{cases} \qquad (5a)$$

For $n \neq 1$

$$f_{1_i}(z') = \begin{cases} \dfrac{\sin\left[K\ (\pm z_o \mp l_z - z')\right]}{\sin(Kl_z)} & \pm z_o \mp l_z \leq z' \leq \pm z_o \\ \\ 0 & \text{Otherwise} \end{cases} \tag{5b}$$

$$(\pm\mp)\ i = \begin{pmatrix} a \\ b \end{pmatrix}$$

where $l_z = Z_{n+1} - Z_n \approx Z_n - Z_{n-1}$. The magnetic current on the coupling

aperture is represented as

$$M_{x_a}(x',0,z') = \sum_{n=1}^{M} V_n\ f_n(x')\ g_o(z') \tag{6}$$

where $f_n(x')$ and $g_o(z')$ are given as equations (7) and (8),

respectively, and the V_m are unknown amplitude coefficients.

$$f_n(x') = \begin{cases} \dfrac{\sin\left[K(x'-x_{n-1})\right]}{\sin(Kl_x)} & x_{n-1} \leq x' \leq x_n \\ \\ \dfrac{\sin\left[K(x_{n+1}-x')\right]}{\sin(Kl_x)} & x_n \leq x' \leq x_{n+1} \\ \\ 0 & \text{Otherwise} \end{cases} \tag{7}$$

$$g_o(z') = \begin{cases} \dfrac{2}{\pi t}\left\{1-\left[\dfrac{2z'}{t}\right]^2\right\}^{-1/2} & -\dfrac{t}{2} \leq z' \leq \dfrac{t}{2} \\ \\ 0 & \text{Otherwise} \end{cases} \tag{8}$$

4

We also see that $l_x = x_{n+1} - x_n = x_n - x_{n-1}$ and

$x_n = (n-1) l_x$. Under these conditions the requirement that the magnetic current is non-zero only on the coupling aperture is satisfied. The next step in the analysis is to obtain the Fourier transforms of (4) and (6). The transforms of interest are written as:

$$K_{z_a}(\alpha, h_a, \tilde{\beta}) = \iint\limits_{-\infty}^{\infty} K_{z_a}(x', h_a, z') \, e^{j\alpha x'} \, e^{j\beta z'} \, dx' dz' \qquad (9)$$

$$K_{z_b}(\alpha, -h_b, \tilde{\beta}) = \iint\limits_{-\infty}^{\infty} K_{z_b}(x', -h_b, z') \, e^{j\alpha x'} \, e^{j\beta z'} \, dx' dz' \qquad (10)$$

$$M_{x_a}(\alpha, 0, \tilde{\beta}) = \iint\limits_{-\infty}^{\infty} M_{x_a}(x', 0, z') \, e^{j\alpha x'} \, e^{j\beta z'} \, dx' dz' \qquad (11)$$

For $\tilde{K}_{z_a}(\alpha, h_a, \beta)$ we obtain

$$\tilde{K}_{z_a}(\alpha, h_a, \beta) = \int\limits_{-\infty}^{\infty} g_a(x') \, e^{j\alpha x'} \, dx' \left[\sum_{n=2}^{N} I_{n_a} \int\limits_{z_{n+1}}^{z_{n-1}} f_n(z') \, e^{j\beta z'} dz' \right.$$

$$\left. + \int\limits_{z_o - l_z}^{z_o} I_{1_a} \, f_1(z') \, e^{j\beta z'} \, dz' + \int\limits_{z_o}^{\infty} \left(e^{\gamma_{z_a}^{ms} z'} - Re^{-\gamma_{z_a}^{ms} z'} \right) \, e^{j\beta z'} \, dz' \right]$$

$$\tilde{K}_{z_a}(\alpha, h_a, \beta) = I_1^a \left[I_2^a + I_3^a + I_4^a \right] \qquad (12)$$

$$I_1^a = \int\limits_{x_a - \frac{w_a}{2}}^{x_a + \frac{w_a}{2}} \frac{2}{\pi w_a} \left\{ 1 - \left[\frac{2(x' - x_a)}{w_a} \right]^2 \right\}^{-1/2} e^{j\alpha x'} \, dx' \qquad (13)$$

5

$$I_2^a = \sum_{n=2}^{N} I_{n_a} \left[\int_{z_{n-1}}^{z_n} \frac{\sin K(z'-z_n-1)}{\sin(Kl_z)} \, e^{j\beta z'} \, dz' + \int_{z_n}^{z_{n+1}} \frac{\sin K(z_{n+1}-z')}{\sin(Kl_z)} \, e^{j\beta z'} \, dz' \right]$$

$$\tag{14a}$$

$$I_3^a = \int_{z_o-l_z}^{z_o} I_{1_a} \, f_1(z') \, e^{j\beta z'} \, dz' \tag{14b}$$

$$I_4^a = \int_{z_o}^{\infty} \left[e^{(\gamma_{z_a}^{ms} + j\beta)z'} - \text{Re}^{(-\gamma_{z_a}^{ms} + j\beta)z'} \right] dz' \tag{15}$$

After some algebra I_1^a, I_2^a, and I_3^a are found to be:

$$I_1^a = e^{j\alpha x_a} \, J_o\left(\alpha \, \frac{w_a}{2} \right) \tag{16}$$

$$I_2^a = \frac{j2\beta}{(K^2-\beta^2)} \sum_{n=2}^{N} I_{n_a} \, e^{j\beta z_n} \tag{17a}$$

$$I_3^a = \frac{I_{1_a} \, e^{j\beta(z_o-l_z)}}{(K^2-\beta^2) \, \sin(Kl_z)} \left[K-e^{j\beta l_z} \, (j\beta \sin Kl_z - k\cos Kl_z) \right] \tag{17b}$$

To evaluate I_4^a, some special considerations are necessary.

I_4^a is written alternatively as

$$I_4^a = \int_{-\infty}^{\infty} u(z'-z_o) \left[e^{(\gamma_{z_a}^{ms} + j\beta)z'} - R e^{(-\gamma_{z_a}^{ms} + j\beta)z'} \right] dz' \tag{18}$$

and we assume a lossless system so that $\gamma_{z_a}^{ms}$ is a purely imaginary

quantity, $\gamma_{z_a}^{ms} = j\, k_{z_a}^{ms}$. The Fourier transform of the product of two

functions is equal to the convolution of the individual Fourier

transforms of the two functions, [6]. Using this idea to evaluate

(18) shows

$$I_4^a = F\left\{ U(z'-z_o) \right\} \,\star\, f\left\{ \left[e^{jk_{z_a}^{ms}z'} - R e^{-jk_{z_a}^{ms}} \right] \right\} \tag{19}$$

$$\int_{-\infty}^{\infty} U(z'-z_o)\, e^{j\beta z'} dz' = \left[\pi\delta(\beta) + \frac{1}{j\beta} \right] e^{j\beta z_o} \tag{20a}$$

$$\int_{-\infty}^{\infty} e^{jk_{z_a}z'} e^{j\beta z'} dz' = 2\pi\delta\left(\beta + k_{z_a}^{ms} \right) \tag{20b}$$

$$-R \int_{-\infty}^{\infty} e^{-jk_{z_a}^{ms}z'} e^{j\beta z'} dz' = -2\pi R\delta\left(\beta - k_{z_a}^{ms} \right) \tag{20c}$$

From equations (19) and (20) we express I_4^a as

$$I_4^a = 2\pi \int_{-\infty}^{\infty} e^{j\lambda z_o} \left[\pi\delta(\lambda) + \frac{1}{j\lambda}\right]\left[\delta\left(\beta-\lambda + k_{z_a}^{ms}\right) - R\delta\left(\beta-\lambda - k_{z_a}^{ms}\right)\right] d\lambda$$

$$= 2\pi \int_{-\infty}^{\infty} \left[\pi e^{j\lambda_o z_o}\, \delta(\lambda)\, \delta\left(\beta-\lambda + k_{z_a}^{ms}\right) + \frac{e^{j\lambda z_o}}{j\lambda}\, \delta\left(\beta-\lambda + k_{z_a}^{ms}\right)\right.$$

$$\left. -\pi R e^{j\lambda z_o}\, \delta(\lambda)\, \delta\left(\beta-\lambda - k_{z_a}^{ms}\right) - \frac{R e^{j\lambda z_o}}{j\lambda}\, \delta\left(\beta-\lambda - k_{z_a}^{ms}\right)\right] d\lambda$$

$$I_4^a = 2\pi^2\, \delta\left(\beta + k_{z_a}^{ms}\right) - 2\pi^2\, R\delta\left(\beta - k_{z_a}^{ms}\right)$$

$$+ 2\pi\left[\frac{-e^{j\left(\beta+k_{z_a}^{ms}\right) z_o}}{j\left(\beta+k_{z_a}^{ms}\right)} + R\, \frac{e^{j\left(\beta-k_{z_a}^{ms}\right) z_o}}{j\left(\beta-k_{z_a}^{ms}\right)}\right] \tag{21}$$

Substituting (16), (17), and (21) into (12) shows:

$$\tilde{K}_{z_a}(\alpha, h_a, \beta) = -\frac{2\pi\, e^{j\alpha x_a}\, e^{-j\left(\beta+k_{z_a}^{ms}\right) z_o}}{j\left(\beta+k_{z_a}^{ms}\right)}\, J_o\left(\alpha\, \frac{W_a}{2}\right)$$

$$+ R\, \frac{2\pi\, e^{j\alpha x_a}\, e^{-j\left(\beta-k_{z_a}^{ms}\right)}}{j\left(\beta-k_{z_a}^{ms}\right)}\, J_o\left(\alpha\, \frac{W_a}{2}\right) + \frac{j2\beta e^{j\alpha x_a}\, J_o\left(\alpha\, \frac{W_a}{2}\right)}{\left(K^2-\beta^2\right)} \sum_{n=2}^{N} I_{n_a}\, e^{j\beta z_n}$$

$$+ I_{1_a}\, \frac{e^{j\alpha x_a}\, e^{j\beta(z_o-l_z)}}{\left(K^2-\beta^2\right) \sin(kl_z)}\, J_o\left(\alpha\, \frac{W_a}{2}\right)\left[K - e^{j\beta l_z}\left(j\beta\sin K\, l_z - k\cos K\, l_z\right)\right]$$

$$+ 2\pi^2\left[\delta\left(\beta+k_{z_a}^{ms}\right) - R\delta\left(\beta-k_{z_a}^{ms}\right)\right] e^{j\alpha x_a}\, J_o\left(\alpha\, \frac{W_a}{2}\right) \tag{22}$$

8

In a completely analogous manner $\tilde{K}_{z_b}(\alpha,-h_b,\beta)$ is found to be

$$
\begin{aligned}
\tilde{K}_{z_b}(\alpha,-h_b,\beta) = &-T\ \frac{2\pi\ e^{j\alpha x_b}\ e^{j\left(\beta+k_{z_b}^{ms}\right)z_o}}{j\left(\beta+k_{z_b}^{ms}\right)}\ J_o\left(\alpha\ \frac{W_b}{2}\right) \\
&+ \frac{I_{1_b}\ e^{j\alpha x_b}\ e^{-j\beta(z_o-1_z)}\ J_o\left(\alpha\ \frac{W_b}{2}\right)}{\left(K^2-\beta^2\right)\ \sin(kl_z)}\left[K + e^{-j\beta l_z}\ (j\beta\sin Kl_z + k\cos Kl_z)\right] \\
&+ \frac{j\beta\ e^{j\alpha x_b}\ J_o\left(\alpha\ \frac{W_b}{2}\right)}{\left(K^2-\beta^2\right)}\ \sum_{n=2}^{N}\ I_{n_b}\ e^{j\beta z_n} + 2\pi^2\ T\ e^{j\alpha x_b}\ J_o\left(\alpha\ \frac{W_b}{2}\right)\ \delta\left(\beta+k_{z_b}^{ms}\right)
\end{aligned}
$$

(23)

The discretized microstrip currents near the discontinuity region are divided in 'N' partitions in both guides 'a' and 'b'. More severe disruption of the current occurs in guide 'a' due to the open end upon which K_{z_a} is incident. If 'N' partitions are required to accurately characterize K_{z_a} then the same number will represent K_{z_b} in its respective discontinuity region.

The Fourier transform of $M_{x_a}(x',0,z')$ is expressed from (6), (7), (8) and (11) as

$$
\tilde{M}_{x_a}(\alpha,0,\beta) = \sum_{n=1}^{M}\ V_n\ \int\!\!\!\int_{-\infty}^{\infty}\ f_n(x')\ g_o(z')\ e^{j\alpha x'}e^{j\beta z'}dx'\ dz' = I_4\cdot I_5
$$

(24)

9

$$I_4 = \int_{-t/2}^{t/2} \frac{2}{\pi t} \left\{ 1 - \left[\frac{2z'}{t} \right]^2 \right\}^{-1/2} e^{j\beta z'} dz'$$

and clearly

$$I_4 = \int_{-t/2}^{t/2} \frac{2}{\pi t} \left\{ 1 - \left[\frac{2z'}{t} \right]^2 \right\}^{-1/2} \left[\cos\beta z' + j\sin\beta z' \right] dz'$$

$$= \int_{-t/2}^{t/2} \frac{2}{\pi t} \left\{ 1 - \left[\frac{2z'}{t} \right]^2 \right\}^{-1/2} \cos\beta z' \, dz'$$

Let

$$\frac{2z'}{t} = \cos\phi \Rightarrow dz' = \frac{-t}{2} \sin\phi \, d\phi$$

$$I_4 = \int_{-t/2}^{t/2} \frac{2}{\pi t} \frac{1}{\sin\phi} \cos\beta\left(\frac{t}{2} \cos\phi \right) - \frac{t}{2} \sin\phi \, d\phi$$

$$I_4 = \frac{1}{\pi} \int_{0}^{\pi} \cos\beta\left(\frac{t}{2} \cos\phi \right) d\phi = J_o\left(\beta \frac{t}{2} \right) \tag{25}$$

$$I_5 = \sum_{n=1}^{M} V_n \int_{X_{n-1}}^{X_{n+1}} f_n(x') \, e^{j\alpha x'} dx' \tag{26}$$

Substituting for $f_n(x')$ from equation (7) and evaluating the result yields

$$I_5 = \sum_{n=1}^{M} V_n \frac{j2\alpha \, e^{j\alpha X_n}}{(K^2 - \alpha^2)} \tag{27}$$

10

Finally then, $\tilde{M}_{x_a}(\alpha, 0, \beta)$ is written as:

$$M_{x_a} = \frac{j2\alpha \; J_o\left(\beta \; \frac{t}{2}\right)}{(K^2 - \alpha^2)} \sum_{n=1}^{M} V_n \; e^{j\alpha x_n} \tag{28}$$

Equations (22), (23), and (28) are very important quantities.

IV. FORMULATION OF THE MATRIX EQUATION

The results obtained in the previous section will allow us to solve equation (1). In the following discussion, spatial and/or spectral dependence of functions will be implied and not explicitly written. If there is any ambiguity, it will be clearly explained from equation (1):

$$\tilde{E}_z^{(1a)} = \tilde{G}_{11} \; \tilde{K}_{z_a} + \tilde{G}_{12} \; \tilde{M}_{x_a} \tag{29}$$

$$\tilde{H}_z^{(1a)} = \tilde{G}_{21} \; \tilde{K}_{z_a} + \tilde{G}_{22} \; \tilde{M}_{x_a} \tag{30}$$

$$\tilde{E}_z^{(1b)} = \tilde{G}_{32} \; \tilde{M}_{x_a} + \tilde{G}_{33} \; \tilde{K}_{z_b} \tag{31}$$

Since, from Appendix A we know that $\tilde{G}_{13} = \tilde{G}_{23} = \tilde{G}_{31} = 0$.

Also, note that the surface current densities are expressed in terms of summations of appropriate basis functions as derived earlier. Before going any further with the analysis it will be convenient to write $\tilde{K}_{z_a}$, $\tilde{K}_{z_b}$, and $\tilde{M}_{x_a}$ as:

11

$$\tilde{K}_{z_a} = -\tilde{k}_o^a + R \, \tilde{k}_1^a + \sum_{n=1}^{N} I_{n_a} \, \tilde{K}_{z_a}^n \qquad (32)$$

$$\tilde{K}_{z_b} = - T \, \tilde{k}_1^b + \sum_{n=1}^{N} I_{n_b} \, \tilde{K}_{z_b}^n \qquad (33)$$

$$\tilde{M}_{x_a} = \sum_{n=1}^{M} V_n \, \tilde{M}_{x_a}^n \qquad (34)$$

where $\tilde{k}_o^a$, $\tilde{k}_1^a$, and $\tilde{K}_{z_a}^n$ are easily deduced from (22). $\tilde{k}_1^b$, $\tilde{K}_{z_b}^n$ and $\tilde{M}_{x_a}^n$

are similarly obtained, respectively, from (23) and (28). We next

multiply equation (29) by $\tilde{K}_{z_a}^q$ and integrate from $-\infty$ to ∞ with

respect to α and β for different values of q. This shows:

$$\iint_{-\infty}^{\infty} \tilde{K}_{z_a}^q \, \tilde{E}_z^{(1a)} d\alpha \, d\beta = \iint_{-\infty}^{\infty} \tilde{K}_{z_a}^q \, \tilde{G}_{11} \, \tilde{K}_{z_a} d\alpha \, d\beta$$

$$+ \iint_{-\infty}^{\infty} K_{z_a}^q \, G_{12} \, \tilde{M}_{x_a} d\tilde{\alpha} \, d\tilde{\beta} \quad q = 1, 2, \ldots, N \qquad (35)$$

but

$$\iint_{-\infty}^{\infty} \tilde{K}_{z_a}^q \, \tilde{E}_z^{(1a)} d\alpha \, d\beta = 0$$

Because, from Parseval's theorem

$$\iint_{-\infty}^{\infty} \tilde{K}_{z_a}^q \, \tilde{E}_z^{(1a)} d\alpha \, d\beta = \frac{1}{(2\pi)^2} \iint_{-\infty}^{\infty} K_{z_a}^q \, E_z^{(1a)} dx \, dz = 0$$

12

Since it is clear that $\tilde{K}_{z_a}^q$ and $\tilde{E}_z^{(1a)}$ are complementary in the

x-direction. Using (32) and (34), equation (35) becomes:

$$\iint\limits_{-\infty}^{\infty} \tilde{K}_{z_a}^q \; \tilde{G}_{11} \left[-\tilde{k}_o^a + R \; \tilde{k}_1^a + \sum_{n=1}^{N} I_{n_a} \; \tilde{K}_{z_a}^n \right] d\alpha d\beta$$

$$+ \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_a}^q \; \tilde{G}_{12} \sum_{n=1}^{M} V_n \; \tilde{M}_{x_a}^n \; d\alpha d\beta = 0 \quad q = 1, 2, \ldots, N$$

$$-\iint\limits_{-\infty}^{\infty} \tilde{K}_{z_a}^q \; \tilde{G}_{11} \; \tilde{k}_o^a \; d\alpha d\beta + \iint\limits_{-\infty}^{\infty} R\left(\tilde{K}_{z_a}^q \; \tilde{G}_{11} \; \tilde{k}_1^a \right) d\alpha d\beta$$

$$+ \sum_{n=1}^{N} I_{n_a} \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_a}^q \; \tilde{G}_{11} \; \tilde{K}_{z_a}^n \; d\alpha d\beta \qquad\qquad (36)$$

$$+ \sum_{n=1}^{M} V_n \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_a}^q \; \tilde{G}_{12} \; \tilde{M}_{x_a}^n \; d\alpha d\beta = 0 \qquad q = 1, 2, \ldots, N$$

Performing similar operations on equations (30) and (31) yields:
From (30)

$$-\iint\limits_{-\infty}^{\infty} \tilde{M}_{x_a}^q \; \tilde{G}_{21} \; \tilde{k}_o^a \; d\alpha d\beta + R \iint\limits_{-\infty}^{\infty} \tilde{M}_{x_a}^q \; \tilde{G}_{21} \; \tilde{k}_1^a \; d\alpha d\beta$$

$$+ \sum_{n=1}^{N} I_{n_a} \iint\limits_{-\infty}^{\infty} \tilde{M}_{x_a}^q \; \tilde{G}_{21} \; \tilde{K}_{z_a}^n \; d\alpha d\beta \qquad\qquad (37)$$

$$+ \sum_{n=1}^{M} V_n \iint\limits_{-\infty}^{\infty} \tilde{M}_{x_a}^q \; \tilde{G}_{21} \; \tilde{M}_{x_a}^n \; d\alpha d\beta = 0 \quad q = 1, 2, \ldots, M$$

13

From (31)

$$
- T \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_b}^q \; \tilde{G}_{33} \; \tilde{k}_1^b \; d\alpha d\beta + \sum_{n=1}^{M} V_n \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_b}^q \; \tilde{G}_{32} \; \tilde{M}_{x_a}^n \; d\alpha d\beta
$$

$$
(38)
$$

$$
+ \sum_{n=1}^{N} I_{n_b} \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_b}^q \; \tilde{G}_{33} \; \tilde{K}_{z_b}^n \; d\alpha d\beta = 0 \qquad q = 1, 2, \ldots, N
$$

Equations (36), (37), and (38) represent an inhomogeneous system of 2N+M equations containing 2N+M+2 unknowns. We get two additional relations by the requirement of electric surface current continuity at $(x=h_a, z=z_o)$ and $(x=-h_b, z=-z_o)$. Look at Figure 2.

From equations (2), (3), (4), and (5) we see

$$
I_{1_a} = e^{jk_{z_a}^{ms} z_o} - R e^{-jk_{z_a}^{ms} z_o} \tag{39a}
$$

$$
I_{1_b} = T e^{-jk_z^{m} z_o} \tag{39b}
$$

Equations (39) represent the necessary relations for solving for R and T. We shall now express (36), (37), and (38) more compactly:

(36) becomes

$$
S_q = R \, P_q + \sum_{n=1}^{N} I_{n_a} D_{qn} + \sum_{n=1}^{M} V_n G_{qn} \qquad q = 1, 2, \ldots, N
$$

where

$$S_q = \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_a}^q \; \tilde{G}_{11} \; \tilde{k}_o^a \; d\alpha d\beta$$

$$P_q = \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_a}^q \; \tilde{G}_{11} \; \tilde{k}_1^a \; d\alpha d\beta \qquad\qquad (40)$$

$$D_{qn} = \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_a}^q \; \tilde{G}_{11} \; \tilde{K}_{z_a}^n \; d\alpha d\beta$$

$$G_{qn} = \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_a}^q \; \tilde{G}_{12} \; \tilde{M}_{x_a}^n \; d\alpha d\beta$$

(37) becomes

$$\$_q = R \; Q_q + \sum_{n=1}^{N} I_{n_a} \; L_{q_n} + \sum_{n=1}^{M} V_n \; F_{q_n} \qquad q = 1, 2, \ldots, M$$

where

$$\$_q = \iint\limits_{-\infty}^{\infty} \tilde{M}_{x_a}^q \; \tilde{G}_{21} \; \tilde{k}_o^a \; d\alpha d\beta$$

$$Q_q = \iint\limits_{-\infty}^{\infty} \tilde{M}_{x_a}^q \; \tilde{G}_{21} \; \tilde{k}_1^a \; d\alpha d\beta \qquad\qquad (41)$$

$$L_{qn} = \iint\limits_{-\infty}^{\infty} \tilde{M}_{x_a}^q \; \tilde{G}_{21} \; \tilde{K}_{z_a}^n \; d\alpha d\beta$$

$$F_{qn} = \iint\limits_{-\infty}^{\infty} \tilde{M}_{x_a}^q \; \tilde{G}_{21} \; \tilde{M}_{x_a}^n \; d\alpha d\beta$$

(38) becomes

$$0 = - T U_q + \sum_{n=1}^{N} I_{n_b} V_{qn} + \sum_{n=1}^{M} V_n X_{qn} \qquad q = 1, 2, \ldots, N$$

where

$$U_q = \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_b}^{q} \ \tilde{G}_{33} \ \tilde{k}_{1}^{b} \ d\alpha d\beta$$

$$V_{qn} = \iint\limits_{-\infty}^{\infty} K_{z_b}^{q} \ G_{33} \ \tilde{K}_{z_b}^{n} \ \tilde{d\alpha d\beta} \qquad\qquad (42)$$

$$X_{qn} = \iint\limits_{-\infty}^{\infty} \tilde{K}_{z_b}^{q} \ \tilde{G}_{32} \ \tilde{M}_{x_a}^{n} \ d\alpha d\beta$$

V. DISCUSSION OF NUMERICAL SOLUTION

It is clear from the results of the last section that the problem under consideration is very difficult. Since no numerical results will be obtained, a discussion of how to do this is in order. Equations (40), (41), and (42) contain integrals which must be evaluated from $-\infty$ to ∞ with respect to two variables: α and β. A brief glance at Appendix A indicates that numerical integration of these terms will surely be required. Although it is not obvious, these integrals vary at worst as $\dfrac{1}{\alpha^{3/2}}$, $\dfrac{1}{\alpha^{2}}$, $\dfrac{1}{\beta^{3/2}}$, $\dfrac{1}{\beta^{2}}$ in one part or another. The squared terms will converge rapidly and the same can be said for the $\dfrac{1}{\alpha^{3/2}}$ and $\dfrac{1}{\beta^{3/2}}$ terms. Ultimately, one would need to program a computer to do these integrations to find

16

how the convergence progresses. However, in [7], Mittra and Itoh discuss so called 'numerically efficient techniques' for solving boundary value problems. The approach used in this report closely resembles the algorithms discussed there. As a result, it would seem that satisfactory convergence is obtainable for the equations derived here. Besides having to evaluate the integrals mentioned, we must also solve a linear system of equations. There are many viable alternatives for this part of the problem and no further discussion is necessary.

VI. CONCLUSION

The solution for reflection and transmission coefficients in slot-coupled microstrip lines has been formulated in the spectral domain. Although no numerical results have been obtained, pretinent numerical considerations have been discussed.

REFERENCES

[1]   T. Itoh and R. Mittra, "Spectral-Domain Approach for
      Calculating the Dispersion Characteristics of Microstrip
      Lines," IEEE Trans. Microwave Theory Tech., vol. MTT-21, No.
      7, pp. 496-499, July 1973.

[2]   T. Itoh, ed., "Planar Transmission Line Structures," IEEE
      Press, 1987.

[3]   P. Katehi and N. Alexopoulos, "Frequency-Dependent
      Characteristics of Microstrip Discontinuities in
      Millimeter-Wave Integrated Circuits," IEEE Trans. Microwave
      Theory Tech., vol. MTT-33, No. 10, pp. 1029-1035, October
      1985.

[4]   L. Dunleavy, Ph.D. thesis, University of Michigan, 1988.

[5]   R. Harrington, "Time-Harmonic Electromagnetic Fields," New
      York: McGraw-Hill, 1961.

[6]   A. Papoulis, "The Fourier Integral and Its Applications," New
      York: McGraw-Hill, 1962.

[7]   R. Mittra, ed., "Computer Techniques in Electromagnetics,"
      pp. 305-342, New York: Pergamon Press, 1973.

Appendix A

Derivation of the Green's matrix

Hybrid mode analysis with

$$\overline{E}(x,y,z) = -j\omega\overline{A} + \frac{1}{j\omega\mu\varepsilon}\nabla\nabla\cdot\overline{A} + \frac{1}{\varepsilon}\nabla\times\overline{F}$$

(A-1)

$$\overline{H}(x,y,z) = j\omega\overline{F} - \frac{1}{j\omega\mu\varepsilon}\nabla\nabla\cdot\overline{F} + \frac{1}{\mu}\nabla\times\overline{A}$$

Choose $\overline{A} = \hat{z}A_z$ and $\overline{F} = \hat{z}F_z$ where

$$A_z^{(i)}(x,y,z) = \frac{1}{(2\pi)^2}\iint\limits_{-\infty}^{\infty}\tilde{A}_z^{(i)}(\alpha,y,\beta)\ e^{-j\alpha x}\ e^{-j\beta z}\ d\alpha d\beta$$

(A-2)

$$\tilde{A}_z^{(i)} = -\left(\frac{\omega\mu\varepsilon}{\beta}\right)\tilde{\psi}_A^{(i)}(\alpha,y,\beta)\quad (i = 1a, 1b, 2a, 2b)$$

$$F_z^{(i)}(x,y,z) = \frac{1}{(2\pi)^2}\iint\limits_{-\infty}^{\infty}\tilde{F}_z^{(i)}(\alpha,y,\beta)\ e^{-j\alpha x}\ e^{-j\beta z}\ d\alpha d\beta$$

(A-3)

$$\tilde{F}_z^{(i)} = \left(\frac{\omega\mu\varepsilon}{\beta}\right)\tilde{\psi}_F^{(i)}(\alpha,y,\beta)\quad (i = 1a, 1b, 2a, 2b)$$

$A_z^{(i)}(x,y,z)$ and $F_z^{(i)}(x,y,z)$ must satisfy

(A-4)
$$\left(\nabla^2 + k_i^2\right)\begin{Bmatrix} A_z^{(i)}(x,y,z) \\[2mm] F_z^{(i)}(x,y,z) \end{Bmatrix} = 0$$

19

Substituting (A-2) and (A-3) into (A-4) implies:

$$\left[\frac{\partial^2}{\partial y^2} - \left(\alpha^2 + \beta^2 - k_i^2\right)\right] \left\{ \begin{array}{c} \tilde{\psi}_A^{(i)}(\alpha, y, \beta) \\[2ex] \tilde{\psi}_F^{(i)}(\alpha, y, \beta) \end{array} \right\} = 0$$

Letting $\gamma_i^2 = \alpha^2 + \beta^2 - k_i^2$ shows

$$(A-5) \qquad \left(\frac{\partial^2}{\partial y^2} - \gamma_i^2\right) \left\{ \begin{array}{c} \tilde{\psi}_A^{(i)}(\alpha, y, \beta) \\[2ex] \tilde{\psi}_F^{(i)}(\alpha, y, \beta) \end{array} \right\} = 0$$

Appropriate solutions to (A-5) in each region of the structure shown in Figure 1 are:

$$\tilde{\psi}_A^{(1a)} = \tilde{A}^{(1a)} \sinh(\gamma_{1a} y) + \tilde{B}^{(1a)} \cosh(\alpha_{1a} y)$$

$$\tilde{\psi}_A^{(2a)} = \tilde{D}^{(2a)} \sinh\left[\gamma_{2a}(y-b)\right]$$

$$(A-6) \qquad \tilde{\psi}_A^{(1b)} = \tilde{A}^{(1b)} \sinh(\gamma_{1b} y) + \tilde{B}^{(1b)} \cosh(\alpha_{1b} y)$$

$$\tilde{\psi}_A^{(2b)} = \tilde{P}^{(2b)} \sinh\left[\gamma_{2b}(y+b)\right]$$

$$\tilde{\psi}_F^{(1a)} = \tilde{C}^{(1a)} \sinh(\gamma_{1a} y) + \tilde{D}^{(1a)} \cosh(\alpha_{1a} y)$$

$$\tilde{\psi}_F^{(2a)} = \tilde{N}^{(2a)} \cosh\left[\gamma_{2a}(y-b)\right]$$

$$(A-7) \qquad \tilde{\psi}_F^{(1b)} = \tilde{C}^{(1b)} \sinh(\gamma_{1b} y) + \tilde{D}^{(1b)} \cosh(\alpha_{1b} y)$$

$$\tilde{\psi}_F^{(2b)} = \tilde{N}^{(2b)} \cosh\left[\gamma_{2b}(y+b)\right]$$

Note: The ~ notation means Fourier transform domain.

The transformed fields must satisfy

$$\tilde{E}_z^{(1q)}(\alpha, h_q, \beta) = \tilde{E}_z^{(2q)}(\alpha, h_q, \beta)$$

$$\tilde{E}_x^{(1q)}(\alpha, h_q, \beta) = \tilde{E}_x^{(2q)}(\alpha, h_q, \beta)$$

$$\tilde{H}_z^{(1q)}(\alpha, h_q, \beta) = \tilde{H}_z^{(2q)}(\alpha, h_q, \beta)$$

(A-8) $\quad \tilde{H}_x^{(1q)}(\alpha, h_q, \beta) - \tilde{H}_x^{(2q)}(\alpha, h_q, \beta) = \tilde{K}_{z_q}(\alpha, h_q, \beta)$

$$\tilde{E}_x^{(1q)}(\alpha, 0, \beta) = 0$$

$$\tilde{E}_z^{(1q)}(\alpha, 0, \beta) = \tilde{M}_x(\alpha, 0, \beta)$$

$$(q = a, b)$$

$\tilde{K}_{z_q}(\alpha, h_q, \beta)$ is the Fourier transform of the electric surface current

on the qth microstrip. $\tilde{M}_x(\alpha, 0, \beta)$ is the Fourier transform of

magnetic surface current on the aperture which is common to the
two microstrip structures.

At this point in the derivation it should be noted that
symmetry about the line x=0, y=0 exists between guides (a) and

(b). In order to derive $\tilde{G}_{11}(\alpha, \beta)$ and $\tilde{G}_{12}(\alpha, \beta)$, we apply the

boundary conditions (A-8) and express $\tilde{E}_z^{(1a)}(\alpha, h_a, \beta)$ appropriately.

$\tilde{G}_{32}(\alpha, \beta)$ and $\tilde{G}_{33}(\alpha, \beta)$ are obtained from, respectively, $\tilde{G}_{12}(\alpha, \beta)$

and $\tilde{G}_{11}(\alpha, \beta)$ as

$$\tilde{G}_{32}(\alpha, \beta) = \tilde{G}_{12}(\alpha, \beta) \Big|_{h_a = -h_b; \ k_{1a} = k_{1b}}$$

(A-9)

$$\tilde{G}_{33}(\alpha, \beta) = \tilde{G}_{11}(\alpha, \beta) \Big|_{h_a = -h_b; \ k_{1a} = k_{1b}}$$

Consequently, solving for $\tilde{G}_{12}(\alpha,\beta)$ and $\tilde{G}_{11}(\alpha,\beta)$ yields $\tilde{G}_{32}(\alpha,\beta)$ and $\tilde{G}_{33}(\alpha,\beta)$ in a direct manner. Imposing the boundary conditions (A-8) and appropriately manipulating terms yields the components of the Green's matrix as:

$$\tilde{G}_{11}(\alpha,\beta) = -j\omega\mu\left(k_{1a}^2 - \beta^2\right)\left(k_{2a}^2 - \beta^2\right) \Bigg/ \Bigg\{ \alpha^2\beta^2\left(k_{1a}^2 - k_{2a}^2\right)^2$$

$$- \gamma_{2a}^2 k_{2a}^2\left(k_{1a}^2 - \beta^2\right) - \gamma_{1a}^2 k_{1a}^2\left(k_{2a}^2 - \beta^2\right)$$

$$+ \gamma_{1a}\gamma_{2a}\left(k_{1a}^2 - \beta^2\right)\left(k_{2a}^2 - \beta^2\right)\Big\{ k_{1a}^2 \tanh\left[\gamma_{2a}(h-b)\right] \coth\left(\gamma_{1a}h_a\right)$$

$$+ k_{2a}^2 \tanh\left(\gamma_{1a}h_a\right) \coth\left[\gamma_{2a}(h_a-b)\right]\Big\} \Bigg\}$$

$$\tilde{G}_{21}(\alpha,\beta) = \frac{-j\alpha\beta\left(k_{2a}^2 - k_{1a}^2\right) \cosh\left(\gamma_{1a}h_a\right) \tilde{G}_{11}(\alpha,\beta)}{\omega\mu\left[\gamma_{2a}\left(k_{1a}^2 - \beta^2\right) \tanh\left[\gamma_{2a}(h_a-b)\right] - \gamma_{1a}\left(k_{2a}^2 - \beta^2\right) \tanh\left(\gamma_{1a}h_a\right)\right]}$$

$$\tilde{G}_{31} = 0$$

$$\tilde{G}_{12}(\alpha,\beta) = \cosh\left(\gamma_{1a}h_a\right) - 2\beta\left(k_{1a}^2 - \beta^2\right)\left(k_{2a}^2 - \beta^2\right)\left(k_{1a}^2 - k_{2a}^2\right)\frac{\tilde{\Gamma}_a\left(\alpha,\beta,h_a\right)}{\tilde{\xi}_a\left(\alpha,\beta,h_a\right)}$$

$$\tilde{\Gamma}_a\left(\alpha,\beta,h_a\right) = \sin\left(\gamma_{1a}h_a\right) \Bigg\{ \tanh\left[\gamma_{2a}(h_a-b)\right] \big[\beta^2\gamma_{2a}\left(k_{1a}^2 - \beta^2\right)\left(k_{2a}^2 + \gamma_{2a}^2\right)$$

$$- \alpha^2\beta^2\gamma_{2a}\left(k_{1a}^2 - k_{2a}^2\right) + \alpha^2\gamma_{2a}\left(k_{1a}^2 + \gamma_{2a}^2\right)\left(k_{1a}^2 - \beta^2\right) - k_{1a}^2\gamma_{2a}^2\left(k_{1a}^2 - \beta^2\right)\big]$$

$$+ \tanh\left(\gamma_{1a}h_a\right) \left[k_{1a}^2\gamma_{2a}^2\gamma_{1a}\left(k_{2a}^2 - \beta^2\right) - \beta^2\gamma_{1a}\left(k_{2a}^2 + \gamma_{2a}^2\right)\left(k_{2a}^2 - \beta^2\right) \right.$$

$$- \alpha^2 \gamma_{1a}\left(k_{1a}^2 + \gamma_{2a}^2\right)\left(k_{2a}^2 - \beta^2\right)\Big] - k_{2a}^2 \gamma_{1a}\gamma_{2a}\left(k_{2a}^2 - \beta^2\right)\coth\left[\gamma_{2a}\left(h_a - b\right)\right]\Big\}$$

$$+ \cosh\left(\gamma_{1a}h_a\right)\left[\alpha^2\beta^2\gamma_{1a}\left(k_{1a}^2 - k_{2a}^2\right) - \gamma_{1a}\gamma_{2a}^2 k_{2a}^2\left(k_{1a}^2 - \beta^2\right)\right]$$

$$\tilde{\xi}_a\left(\alpha, \beta, h_a\right) = \alpha^2\beta^2\left(k_{1a}^2 - k_{2a}^2\right)^2 + k_{2a}^2\gamma_{2a}^2\left(k_{1a}^2 - \beta^2\right)^2 + k_{1a}^2\gamma_{1a}^2\left(k_{2a}^2 - \beta^2\right)^2$$

$$+ \gamma_{1a}\gamma_{2a}k_{2a}^2\left(k_{2a}^2 - \beta^2\right)\left(k_{1a}^2 - \beta^2\right)\tanh\left(\gamma_{1a}h_a\right)\coth\left[\gamma_{2a}\left(h_a - b\right)\right]$$

$$- \gamma_{1a}\gamma_{2a}k_{1a}^2\left(k_{2a}^2 - \beta^2\right)\left(k_{1a}^2 - \beta^2\right)\coth\left(\gamma_{1a}h_a\right)\tanh\left[\gamma_{2a}\left(h_a - b\right)\right]$$

$$\tilde{G}_{22}(\alpha, \beta) = \tilde{\eta}(\alpha, \beta)\Big/ \tilde{\tau}(\alpha, \beta)$$

where

$$\tilde{\eta}(\alpha, \beta) = -j\left\{\frac{\sinh\left(\gamma_{1a}h_a\right)}{\omega^2\mu\gamma_{1a}\left(k_{2a}^2 - \beta^2\right)}\left[\beta^2\left(k_{1a}^2 - k_{2a}^2\right) - \left(k_{1a}^2 + \gamma_{2a}^2\right)\left(\alpha^2 + \beta^2\right) + k_{1a}^2\gamma_{2a}^2\right]\right.$$

$$\left. + \frac{\omega\epsilon_{1a}\gamma_{1a}}{\left(k_{1a}^2 - \beta^2\right)}\cosh\left(\gamma_{1a}h_a\right)\coth\left(\gamma_{1a}h_a\right)\right\} \times \left\{\alpha\beta\left(k_{1a}^2 - k_{2a}^2\right)\Big/\right.$$

$$\left.\left[\epsilon_{2a}\gamma_{2a}\left(k_{1a}^2 - \beta^2\right)\coth\left[\gamma_{2a}\left(h_a - b\right)\right] - \epsilon_{1a}\gamma_{1\alpha}\left(\kappa_{2\alpha}^2 - \beta^2\right)\coth\left(\gamma_{1a}h_a\right)\right]\right\}$$

$$+ j\alpha\beta\left[\frac{2}{\left(k_{1a}^2 - \beta^2\right)}\cosh\left(\gamma_{1a}h_a\right) - \frac{\gamma_{2a}\sinh\left(\gamma_{1a}h_a\right)}{\gamma_{1a}\left(k_{2a}^2 - \beta^2\right)}\tanh\left[\gamma_{2a}\left(h_a - b\right)\right]\right]$$

$$\tilde{\tau}(\alpha,\beta) = \frac{j\cosh\left(\gamma_{1a}h_a\right)}{\left(k_{2a}^2 - \beta^2\right)} \left\{ \frac{\omega\mu}{\beta} \left[\gamma_{2a}\left(k_{1a}^2 - \beta^2\right) \tanh\left[\gamma_{2a}\left(h_a - b\right)\right] \right. \right.$$

$$\left. - \gamma_{1a}\left(k_{2a}^2 - \beta^2\right) \tanh\left(\gamma_{1a}h_a\right) \right] - \frac{\alpha^2\beta}{\omega}\left(k_{1a}^2 - k_{2a}^2\right)^2 \Bigg/ \left[\varepsilon_{2a}\gamma_{2a}\left(k_{1a}^2 - \beta^2\right) \cdot \right.$$

$$\left. \left. \coth\left[\gamma_{2a}\left(h_a - b\right)\right] - \varepsilon_{1a}\gamma_{1a}\left(k_{2a}^2 - \beta^2\right) \coth\left(\gamma_{1a}h_a\right) \right] \right\}$$

$\tilde{G}_{32}(\alpha,\beta)$ is obtained through equation A-9.

$$\tilde{G}_{13}(\alpha,\beta) = 0$$

$$\tilde{G}_{23}(\alpha,\beta) = 0$$

$\tilde{G}_{33}(\alpha,\beta)$ is obtained through equation A-9.